Panasonic ideas for life

AV-HS410 Live Switcher

**Preliminary** 





High-End Performance and Functions in a Compact, Integrated Body Expandable 1ME Switcher with Enhanced User Interface, Stereo 3D Compatibility and SDK Offer

The AV-HS410 is an HD/SD selectable 1ME Switcher that rivals many high-end switchers by incorporating a host of inputs and outputs, effects and system expandability into its compact, 19 type, half-rack size. It comes standard with 9 inputs and can increase a maximum capacity of 13 inputs when optional boards are mounted. It provides versatile effects, including transitions with digital video effects and Primatte® chroma keying. Its 177.8 mm (7 inches) color LCD monitor improves operability by an easy-to-see setting screen, new video memory, Memory Preview, enhanced MultiViewer functions, and a button layout that is designed to simplify live relay operation. Addition of an optional board allows stereoscopic 3D image switching and 3D shooting assist.\* Open SDK supports the expansion of plug in software-based functions.

## HD/SD Multi-Format with 9 Inputs Standard, 13 Inputs Maximum

- HD/SD multi-format support, including 1080/24PsF.
   System frequency: 60 Hz/50 Hz/24 Hz switchable.
- Standard inputs: 8 SDI (HD/SD) and 1 DVI-D.
   Standard outputs: 5 SDI (HD/SD) and 1 DVI-D.
- Two optional board slots. Usable for input and/or output, allowing expansion to a maximum of 13 inputs or 10 outputs.
- All input channels feature frame synchronizer.
- Equipped with 4 up-converter channels, 8 dot by dot channels, and 8 video processing channels.
- Features 4 Aux buses. Aux 1 is equipped with a Mix transition function. Flexible operation is enabled by combining Aux buses and M/E sections.

### New Memory Functions and Versatile, High-Quality Effects

- Versatile effect functions. In addition to standard wipe, mix and cut effects, DVE functions, such as reduce, slide, squeeze and 3D wipe are provided.
- Real-time, high-quality chroma keying with the Primatte® algorithm.
- Shot memory and event memory.
- The new Video Memory function allows recording and playback of 2 inputs for still or moving pictures with key signals.
- The new Memory Preview function improves live relays by providing previews of shot memory and event memory image effects.
- An SDHC Memory Card can be used to upload and write still or moving picture data, and to save switcher setting data.

# Compact, Integrated Design Enhances and Advanced Live Relay Operation

- The compact, 19 type rack size is achieved by integrating the control panel and processer unit.
- Built-in 177.8 mm (7 inches) color LCD monitor with WVGA (800 x 480) display. Enables display of menus, input/output images, waveforms and MultiViewer functions.
- Enhanced MultiViewer display enables 4/5/6/9/10/16 split screens, clock display, audio level meter display, and 4:3 marker display.
- The simple panel layout allows direct control of numerous functions.
- 12 crosspoint buttons in each A bus and B bus (maximum of 22 with the Shift function).
- Various functions can be assigned to 8 user buttons.
- Provision of a Software Development Kit (SDK) allow flexible expansion of software-based functions.

### Real 3D Image Switching is Supported

- Mounting the AV-HS04M7D Optional Board enables standard switching of 4 stereoscopic 3D images (L/R pairs), and a maximum of 5.
- L/R mixed output. Three modes (LRMIXa, LRMIXb, and LRDiff) allow easy checking of stereoscopic 3D image parallax.
- Primatte® chroma key composition with of stereoscopic 3D images (L/R pairs).
- Mirror display (vertical/horizontal reversal) and positioning correction of each channel helps to compensate rig-type 3D shooting.
- 3D live relay and 3D production are supported by status monitor display (luminance, RGB distribution, LR difference, and grid) of 3D image signals.

\*Stereoscopic 3D functions are scheduled for release in February 2012. The AV-HS04M7D Option Board and a version update are required for using 3D functions.

### **Panasonic**

Panasonic Corporation Business Solutions Business Group 2-15 Matsuba-cho, Kadoma, Osaka 571-8503 Japan

http://pro-av.panasonic.net

#### [Countries and Regions]

Argentina

Iran

+61 2 9986 7400 +973 252292 Bahrain +32 (0) 2 481 04 57 +55 11 3889 4035 Belaium Brazil Canada +1 905 624 5010 China +86 10 6515 8828 Hona Kona +852 2313 0888 Czech Republic +420 236 032 552/511 +45 43 20 08 57 Denmark Egypt Finland, Latvia, +20 2 23938151 ithuania, Estonia +358 (9) 521 52 53 France +33 (0) 1 55 93 66 67 Germany, Austria +49 (0)611 235 0 Greece +30 210 96 92 300 Hungary +36 (1) 382 60 60 India +91 120 247 1000 +62 21 385 9449 Indonesia

+54 1 308 1610

(Vida) +98 21 2271463 (Panasonic Office) +98 2188791102 Italy +39 02 6788 367 Jordan +962 6 5859801 Kazakhstan +7 727 298 0891 Korea +82 2 2106 6641 Kuwait +96 522431385

+96 11665557 Lebanon +60 3 7809 7888 +52 55 5488 1000 Mexico Netherlands +31 73 64 02 577 +64 9 272 0100 New Zealand Norway +47 67 91 78 00 Pakistan +92 5370320 (SNT) Palestine +972 2 2988750 +507 229 2955 +51 1 614 0000 Panama Peru Philippines +63 2 633 6163 +48 (22) 338 1100 Portugal +351 21 425 77 04 +1 787 750 4300 +40 21 211 4855 Puerto Rico Romania Russia & CIS +7 495 6654205 Saudi Arabia +96 626444072 Singapore +65 6270 0110 Slovak Republic +421 (0) 2 52 92 14 23 Slovenia, Albania, Bulgaría, Serbia,

Croatia, Bosnia, Macedonia, Montenegro +36 (1) 382 60 60 South Africa +27 11 3131622 Spain +34 (93) 425 93 00 Sweden +46 (8) 680 26 41 Switzerland +41 (0) 41 259 96 32 Syria +963 11 231842214 Taiwan +886 2 2227 6214
Thailand +66 2 731 8888
Turkey +90 216 578 3700
U.A.E. (for All Middle East)
+971 4 8862142

Ukraine +380 44 4903437 U.K. +44(0)1344 70 69 13 U.S.A. +1 877 803 8492 Vietnam +848 38370280







Factories of Business Solutions Business Group have received ISO14001:2004-the Environmental Management System certification. (Except for 3rd party's peripherals.)

<sup>\*</sup> Primatte® is a registered trademark of IMAGICA DIGIX Inc. The copyrights of Primatte® belong to IMAGICA DIGIX Inc. The patents for Primatte® also belong to IMAGICA DIGIX Inc.